

NL-4865

4" Square Gimbal Trim

Source: 50W Max.
MR16

Type

Project

Catalog No.

Notes

FEATURES

Trim: Metal trim with adjustable ring can be adjusted up to 43°. Adjustable ring allows lamp to be mounted on top of the trim.

Mounting: Trim includes three trim clips that securely mount trim in housing.

COMPATIBLE HOUSINGS

Compatible with Line Voltage and Low Voltage housings. See individual specification sheets for more information.

COMPATIBLE LAMP / HOUSINGS

Low Voltage:

20W MR16 max. (NL-4010AT/20; NLIC-4010SAT/20; NLR-4040AT/20; NLR-405AT/20; NLIC-402SAT/20; NL-402S/20; NLR-403S/20)
37W MR16 max. (NL-4010AT/37; NLIC-4010SAT/37; NLR-4040AT/37; NLR-405AT/37; NLIC-4020SAT/37; NL-402S/37; NLR-403S/37)
50W MR16 max. (NLIC-401AT/1EL; NLIC-401AT/2EL; NLIC-4010SAT; NL-401AT/1EL; NL-401AT/2EL; NL-4010AT; NLR-404AT/1EL;
NLR-404AT/2EL; NLR-4040AT; NLR-405AT; NLIC-402AT/1EL; NLIC-4020SAT; NL-402S/1EL; NL-402S; NLR-403S/1EL; NLR-403S)
75W MR16 max. (NL-401/75/1EL; NL-401/75/2EL; NL-401/75; NLR-404/75/1EL; NLR-404/75/2EL; NLR-404/75)

Line Voltage:

20W MR16 max. (NSEIC-407AT/20; NSERIC-407AT/20)
25W MR16 max. (NFBIC-401AT/25A)
50W MR16 GU10 max. (NSL-401AT/10; NSLIC-401AT/10; NSLR-404AT/10)


IMPORTANT: DO NOT USE GLASS LENS WHEN ALREADY USING LAMP WITH GLASS COVER

LISTINGS

cULus Listed for Damp Locations



PRODUCT IMAGES AND DIMENSIONS



Compatible Housings

Catalog No.

Low Voltage

- NLIC-4010SAT/20** = ICAT New Construction / 120V Magnetic / 20W
- NLIC-4010SAT/37** = ICAT New Construction / 120V Magnetic / 37W
- NLIC-4010SAT** = ICAT New Construction / 120V Magnetic / 50W
- NLIC-401AT/1EL** = ICAT New Construction / 120V Electronic / 50W
- NLIC-401AT/2EL** = ICAT New Construction / 120V Electronic / 50W
- NL-4010AT/20** = Non-IC AT New Construction / 120V Magnetic / 20W
- NL-4010AT/37** = Non-IC AT New Construction / 120V Magnetic / 37W
- NL-4010AT** = Non-IC AT New Construction / 120V Magnetic / 50W
- NL-401/75** = Non-IC New Const. / 120V Magnetic / 75W
- NL-401AT/1EL** = Non-IC AT New Construction / 120V Electronic / 50W
- NL-401AT/2EL** = Non-IC AT New Construction / 277V Electronic / 50W
- NL-401/75/1EL** = Non-IC New Construction / 120V Electronic / 75W
- NL-401/75/2EL** = Non-IC New Construction / 277V Electronic / 75W
- NLIC-4020SAT/20** = ICAT Shallow New Construction / 120V Magnetic / 20W
- NLIC-4020SAT/37** = ICAT Shallow New Construction / 120V Magnetic / 37W
- NLIC-4020SAT** = ICAT Shallow New Construction / 120V Magnetic / 50W
- NLIC-402AT/1EL** = ICAT Shallow New Construction / 120V Electronic / 50W
- NL-402S/20** = Non-IC Shallow New Construction / 120V Magnetic / 20W
- NL-402S/37** = Non-IC Shallow New Construction / 120V Magnetic / 37W
- NL-402S** = Non-IC Shallow New Construction / 120V Magnetic / 50W
- NL-402S/1EL** = Non-IC Shallow New Construction / 120V Electronic / 50W
- NLR-403S/20** = Non-IC Shallow Remodel / 120V Magnetic / 20W
- NLR-403S/37** = Non-IC Shallow Remodel / 120V Magnetic / 37W
- NLR-403S** = Non-IC Shallow Remodel / 120V Magnetic / 50W
- NLR-403S/1EL** = Non-IC Shallow Remodel / 120V Electronic / 50W
- NLR-4040AT/20** = Non-IC AT Remodel / 120V Magnetic / 20W
- NLR-4040AT/37** = Non-IC AT Remodel / 120V Magnetic / 37W
- NLR-4040AT** = Non-IC AT Remodel / 120V Magnetic / 50W
- NLR-404/75** = Non-IC Remodel / 120V Magnetic / 75W
- NLR-404AT/1EL** = Non-IC AT Remodel / 120V Electronic / 50W
- NLR-404AT/2EL** = Non-IC AT Remodel / 277V Electronic / 50W
- NLR-404/75/1EL** = Non-IC Remodel / 120V Electronic / 75W
- NLR-404/75/2EL** = Non-IC Remodel / 277V Electronic / 75W
- NLR-405AT/20** = Non-IC AT Remodel / No Transformer / 20W
- NLR-405AT/37** = Non-IC AT Remodel / No Transformer / 37W
- NLR-405AT** = Non-IC AT Remodel / No Transformer / 50W

Line Voltage

- NSEIC-407AT/20** = ICAT LED New Construction / 20W
- NSERIC-407AT/20** = ICAT LED Remodel / 20W
- NFBIC-401AT/25A** = Fire Rated IC Air-Tight New Construction / 25W
- NSLIC-401AT/10** = ICAT New Construction / 50W
- NSL-401AT/10** = Non-IC Air-Tight New Construction / 50W
- NSLR-404AT/10** = Non-IC Air-Tight Remodel / 50W

4" Square Gimbal Trim

Catalog No.

- NL-4865B** = 4" Square Gimbal Trim, Black finish
- NL-4865BZ** = 4" Square Gimbal Trim, Bronze finish
- NL-4865N** = 4" Square Gimbal Trim, Natural Metal finish
- NL-4865WW** = 4" Square Gimbal Trim, White finish

Example: **NL-4865WW** = 4" Square Gimbal Trim, White finish