

NTH-147

PAR30 Front Loading Gimbal Ring

Lamp: 75W PAR30 max.

Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT DESCRIPTION

Line voltage PAR adjustable gimbal ring affixed to socket cup to allow lamp installation and removal from the front of the fixture, rather than having to clip the lamp into a ring. A steel yoke holds the gimbal ring in place and allows for full lateral aiming adjustment with high friction hold on vertical angle.

FEATURES

- Deep drawn steel socket cup housing for high strength and rigidity
- Heat resistant Teflon coated wire lead
- Low profile gimbal ring with minimal profile
- Adjustable yoke for custom aiming
- High-strength stainless steel electrical contacts
- One or two circuit track capable

CONSTRUCTION

Housing Socket Cup: 0.025" Deep drawn steel construction with softened edges.

Gimbal Ring: 0.030" Baked enamel finished steel ring with dual brackets spot welded to socket cup enclosure.

Yoke: 0.085" Rigid steel "wishbone" yoke connects fixture housing to electrical contact head. Dual semi tubular rivets and friction washers provide secure hold for vertical angle.

ELECTRICAL

Voltage: 120V input

Socket: Medium base

Lamp: 75W PAR30 max. (not included)

FINISH

Available in black and white finishes.

ONE/TWO CIRCUIT CONVERSION


Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

LABELS AND LISTINGS

UL Listed



PRODUCT IMAGES AND DIMENSIONS



PAR30 Front Loading Gimbal Ring

Catalog No.	Finishes	Style
NTH-147	B = Black	(blank) = H-style
	W = White	/J = J-style
		/L = L-style

Example: NTH-147B = PAR30 Front Loading Gimbal Ring, Black Finish, H-Style Adapter