

NL-641

6" Designer Step Baffle with White Metal Ring

Type _____

Project _____

Catalog No. _____

Notes _____

FEATURES

Trim: Metal trim with 3-1/2" precision spun 0.040 aluminum baffle with deep grooves to reduce aperture glare. Non-reflective painted finishes. Gimbal ring allows lamp to be mounted on top of the trim and adjustable up to 35°.

Mounting: Trim includes two "V" torsion springs to mount trim securely to housing. Replacement "V" torsion springs are available (NRA-86).

COMPATIBLE LAMP / HOUSINGS

Low Voltage:

20W-50W 12V MR16 (NLIC-601 Series; NL-601 Series; NLR-604 Series)
20W-75W 12V MR16 (NL-601/75 Series; NLR-604/75 Series)

Retrofit Kits:

50W 120V MR16 GU10 Max. (NRA-34/10)
20W-50W 12V MR16 (NLK-2600; NLK-2600/EL)


See individual housing specification sheets for more information.

LABELS AND LISTINGS

cULus Listed for Damp Location when used with compatible housing



PRODUCT IMAGES & DIMENSIONS



Compatible Housings

Catalog No. _____

Low Voltage

- NL-6010 = Non-IC New Construction / 120V Magnetic / 20W-50W max
- NL-601/1EL = Non-IC New Construction / 120V Electronic / 3W-50W max
- NL-601/2EL = Non-IC New Construction / 277V Electronic / 20W-50W max
- NL-601/750 = Non-IC New Construction / 120V Magnetic / 20W-75W max
- NL-601/75/1EL = Non-IC New Construction / 120V Electronic / 20W-75W max
- NL-601/75/2EL = Non-IC New Construction / 277V Electronic / 20W-75W max
- NLIC-6010AT = ICAT New Construction / 120V Magnetic / 20W-50W max
- NLIC-601/1EL = ICAT New Construction / 120V Electronic / 3W-50W max
- NLIC-601/2EL = ICAT New Construction / 277V Electronic / 20W-50W max
- NLR-6040 = Non-IC Remodel / 120V Magnetic / 20W-50W max
- NLR-604/1EL = Non-IC Remodel / 120V Electronic / 3W-50W max
- NLR-604/2EL = Non-IC Remodel / 277V Electronic / 20W-50W max
- NLR-604/750 = Non-IC Remodel / 120V Magnetic / 20W-75W max
- NLR-604/75/1EL = Non-IC New Construction / 120V Electronic / 20W-75W max
- NLR-604/75/2EL = Non-IC New Construction / 277V Electronic / 20W-75W max

Low Voltage Retrofit Kits

- NLK-2600 = Non-IC / 120V Magnetic
- NLK-2600/EL = Non-IC / 120V Electronic

Line Voltage Retrofit Kit

- NRA-34/10 = Non-IC / Without Lamp

6" Designer Step Baffle with White Metal Ring

Catalog No. _____

NL-641W = 6" White Designer Step Baffle with White Metal Ring

Example: NL-641W = 6" White Designer Step Baffle with White Metal Ring