

45W LED Retrofit Lamp

Order Code: LP94209



Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Feature & Benefits

- Energy Savings Replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

Applications

- Post top
- Wallpack
- · Area lighting
- · Flood lighting
- Garage lighting
- · General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -40°F and 122°F (-40°C and 50°C)
- Suitable for use in open and enclosed luminaires
- Suitable for use in dry and damp environments
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire
- Lamps have clear polycarbonate cover lenses

Warranty

For warranty information refer to: www.venturelighting.com/resources/warranties

Product Performance	
Input Power (W)	45
Bare Lamp Lumens	6300
DLC Rated Lumens	5830
Lumens/Watt (Bare Lamp)	120
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours	50000
Min. Lamp Compartment (H x L x W)	17.4" x 9.3" x 9.3" (442mm x 236mm x 236mm)
Dimming	No
Operating Temperature Range	-40°F to 122°F (-40°C to 50°C)
Physical Characteristics	
Base Type	Mogul (EX39)
Overall Length A	11.34" (288mm)
Diameter B	3.66" (93mm)
Weight	2.1 lbs (955 g)
Electrical Characteristics	
Input Voltage Range	100-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	≥ 90%
THD	<u>≤</u> 20%
Regulatory Qualifications	
cULus Listed (UL 1993/CSA C22.2 No. 1993)	
cULus Classified (UL 1598C/CSA C22.2 No. 250.1)	
Accessories	


Revision: 04, 29-Nov 2023






SP12714 120-277V Surge Protector

Venture 45W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

(800) 451-2606

6675 Parkland Blvd., Suite 100 Solon, Ohio 44139 USA

 ${\it Email: Venture_Lighting@VentureLighting.com}$

VentureLighting.com

